
Inteligentna Elektronika

Ul. Raduńska 36A
83-333 Chmielno

Tel.: +48 730 90 60 90

E-mail: info@centrumprojektacji.pl



Nazwa	Monitor Interaktywny BenQ RP8602
-------	---

Cena	0,00 zł
------	----------------

Producent	BenQ
-----------	-------------

OPIS PRODUKTU

Specyfikacje

Panel

Screen Size

86"

Resolution (pixels)

UHD 3840 x 2160 pixels

Backlight / Lightsource

DLED

Brightness (Typical) (nits)

400 nits

Contrast Ratio (Typical)

1,200:1

Viewing Angle (Horizontal / Vertical)

178°/178°

Light Life (Typical) (hours)

30,000 hours

Display Orientation

Landscape

Color Gamut (x% NTSC)

68%

Response Time (ms)

8ms

Touch

Touch Technology

IR

Touch Interface

USB B Touch Port x3

Glass

Tempered Glass

4mm Tempered Glass

Anti-Glare & Germ-Resistant Screen

Yes

Connectivity & Sensor

Connector

VGA x1, HDMI 2.0 x3, HDMI Out x1, 3.5mm Audio Line in/Mic in x1, 3.5mm Audio Line out x1, SPDIF Audio out x1, USB 2.0 x3, USB 3.0 x2, USB B Touch Port x3, Type C x1, RS232 x1, RJ45 x1, OPS Slot x1

Built-in Camera

No

Built-in Microphone

Array Microphone x8

Built-in speaker

Speakers 16W x2 & Subwoofer 15W x1

Sensor

NFC Sensor x1, Motion Sensor (PIR) x3, Air Quality Sensor x1, Light Sensor x1

Power

Voltage

AC 100-240V~ 50/60Hz

Mechanical

Weight (Without Packing / With Packing) (kg)

79 kg

Dimension (WxHxD) (mm)

1988.8 x 1229.8 x 138.4

Wall Mounting (VESA) (mm)(Screw type /Max. length)

4 holes (600 x 400mm) Screw M8 x 20mm

Handle

x4

Language

On-Screen Display Languages

English / French / German / Dutch / Polish / Russian / Czech / Danish / Swedish / Italian / Romanian /

Finnish / Norwegian / Greek / Hungarian / Spanish / Portuguese / Traditional Chinese / Simplified /

Chinese / Arabic / Japanese / Thai / Persian / Vietnamese / Korea / Turkey / indonesia (27L)

Package/Accessory

Cable

VGA x1, HDMI x1, USB for touch x1, TYPE-C x1

Quick Start Guide

x1

User's Manual (electronic file)

x1

Wall Mount (with shipment)

x1

Touch Pen

x2

Power Cord

By Region

Remote Controller (with 2.4G dongle & Battery)

x1